

HII NA HE AGC

Low Noise Amplifier

2 - 50 MHz 30 dB Gain



P/N: HII NA-HF-AGC

HILNA-HF-AGC-M/F (with mounting flanges)

NuWaves' HILNA HF AGC is a broadband low noise amplifier, featuring Automatic Gain Control (AGC), designed to achieve high gain while maintaining low noise and a high third-order intercept point in the High Frequency (HF) bands.

This high-performance module delivers 30 dB of gain across the entire broad range of 2 to 50 MHz with an OIP3 of +30 dBm and a P1dB of +18 dBm. This HILNA™ model is also available without Automatic Gain Control (AGC); see the HILNA HF for details.

The HILNA HF's robust power supply also operates over a very broad range, easily allowing the unit to be integrated into systems without regard to power supply precision.

Features

- 2 to 50 MHz
- Broadband Operation
- Low Noise and High Gain
- · High Intercept Point
- Programmable AGC
- Rugged Chassis
- Over-Voltage Protection
- Reverse-Voltage Protection
- Wide Input Voltage Range
- Internal Regulator/Active Bias Devices for Stability

Benefits

- Low Level Signal **Amplification**
- Improved Link Margin
- Ruggedized Chassis for Harsh Environments

Applications

- Wideband RF Front Ends
- General Purpose Amplification
- High Performance Receivers
- Broadband High Gain Block
- Low Noise Transmit Driver
- · RF Preamplifier
- RF Repeater
- Base Station LNA
- University Research and Instruction
- Multi-Signal Environment Amplifier

HILNA HF AGC Low Noise Amplifier

Specifications

Absolute Maximums

| Parameter | Rating | Unit |
|----------------------------------|--------|------|
| Max Device Voltage | 30 | V |
| Max Device Current | 300 | mA |
| Max RF Input Power, $Z_L = 50 Ω$ | 12 | dBm |
| Max Operating Temperature | 70 | °C |
| Max Storage Temperature | 85 | °C |

Export Classification
EAR99

Electrical Specifications @ 12 VDC, 25 °C, Z₅=Z₁=50 Ω

| Parameter | Symbol | Min | Тур | Max | Unit | Condition |
|-----------------------------------|-----------------|-----|-------|-----|------|----------------|
| Operating Frequency | BW | 2 | | 50 | MHz | |
| RF Gain | G | | 30 | | dB | |
| Reverse Isolation | | | 53 | | dB | |
| VCIA/D | VCMD | | 1.5:1 | | | Input |
| VSWR | VSWR | | 1.5:1 | | | Output |
| Noise Figure | NF | | | 5 | dB | |
| Third Order Order Intercept Point | OIP3 | | +30 | | dBm | |
| Output Power @ 1dB Compression | P1dB | | +18 | | dBm | |
| Operating Voltage | VDC | 12 | 12 | 30 | V | |
| Operating Current | I _{DD} | | 150 | 300 | mA | @ 12 VDC (typ) |

Mechanical Specifications


| The enterned to be defined to the | | | | | |
|--------------------------------------|--------------------|------|--------|--|--|
| Parameter | Value | Unit | Limits | | |
| Dimensions | 3.15 x 2.50 x 1.18 | in | Max | | |
| Weight | 5.0 | 0Z | Max | | |
| RF Bulkhead Connector | SMA Female | | | | |
| RF Input and Output Mating Connector | SMA Male | | | | |
| DC Power Connector | Micro-DB9 | | | | |

Environmental Specifications

| | | | _ | | |
|--|------------------|-----|------------|----------------------|------|
| Parameter | Symbol | Min | Тур | Max | Unit |
| Operating Temperature | Tc | -20 | | +60 | °C |
| Storage Temperature | T _{STG} | -40 | | +85 | °C |
| Relative Humidity (non-condensing) | RH | | | 95 | % |
| Altitude MIL-STD-810F - Method 500.4 | ALT | | | 30,000 | ft |
| Tation / Shock Profile andom profile in x,y, z axis, as per Figure for minute duration in each axis) O.04 g/Hz O.04 g/Hz | | | g/Hz ४८ | B _{foctave} | |
| | | 20 | 80 | 350 | 2000 |

HILNA HF AGC Low Noise Amplifier

Mechanical Outline



Accessory Part Numbers - Sold Separately

| Part Number | Description |
|------------------|--|
| NW-LN-ACC-CB09MD | Standard Interface Cable Assembly – Flying Leads |
| NW-LN-ACC-CT09MD | Upgraded Interface Cable Assembly – Banana Plug Termination |

Pinout

| Function | I/O | Pin |
|---------------------------|-----|---------|
| Transmit Data | 0 | 1 |
| Ground | | 2, 6, 7 |
| No Connect | - | 3, 4 |
| Receive Data | I | 5 |
| DC Power (+12 to +30 VDC) | | 8,9 |

For information on product disposal (end-of-life), please refer to this document: https://nuwaves.com/wp-content/uploads/Product-Disposal-End-of-Life.pdf

Contact NuWaves



NuWaves RF Solutions 132 Edison Drive Middletown, OH 45044

www.nuwaves.com sales@nuwaves.com 513.360.0800



Micro-D DB9